

This info is from fellow COPA member Dane Knowlton....

- 1) Connect to Lenovo USB port and to your USB port on your PC
- 2) When you do this, you will see a small USB symbol in the upper left corner.
- 3) Swipe down on that corner where the symbol appears
- 4) The first line should state "USB CONNECTED"
- 5) Touch this (it also states " touch to copy files to/from your computer").
- 6) When you touch the "USB CONNECTED" the next screen will have a "button" that states "Turn on USB Storage", press this and you should see the TU-6718 show up in the directory on the computer. The pictures end up in the folder "DCIM/camerafisamples", I renamed that folder "PICS".

The Droid states to un-mount from the computer prior to turning off USB STORAGE... just in case the USB data gets erased as it may do sometimes. I just unplug and the Droid turns off USB Storage automatically.

Oh one other thing, when you connect the USB cable from the PC, you will see in that same corner "USB debugging connected" scroll by, this has to be connected so be sure that is happening. You can also verify this once you swipe down on that USB symbol.

One more thing, this has to be done every time you connect that Droid to a PC....

AND... you need to be sure that when you go to "settings" in the Droid, select "Storage" and then click the three dots in the upper right corner, click on this and USB Computer connection will show, touch this and assure "Mass storage device (MSC) is selected. This will remain once selected, no need to ever do this again.

That's all there is to it!

Dane